



KRAMER

920

Power Amplifier (200W into 70V/100V)

| Microphone - 3.5/6.5mm | Speakers



The 920 is a high-performance 70V/100V power amplifier for balanced, unbalanced stereo and microphone inputs

FEATURES

- 200W Single Channel Power Amplifier
- 70V or 100V Amplification
- Balanced, Unbalanced and Microphone Inputs
- Input Level Sensitivity Adjustment
- Selectable Microphone 48V Phantom Power
- Selectable High-Pass Filter
- Class D Amplifier



KRAMER

TECHNICAL SPECIFICATIONS

INPUT:	1 balanced stereo +4dBu/10k Ω on a 5-pin removable terminal block, 1 unbalanced stereo on 2 RCA connectors
OUTPUT:	1 speaker 70/100V output on a 3-pin removable, large terminal block
INPUT SENSITIVITY:	0.3V to 1.23V, -10dBu to 4dBu
OUTPUT POWER:	200W
AMPLIFIER TYPE:	Class D
MAXIMUM VOLTAGE GAIN:	+26dB
BANDWIDTH (-3dB):	20Hz to 20kHz
S/N RATIO:	-75dB @14dBu amplification (0.039%)
CONTROLS:	Screw trimmer for line and mic input sensitivity
HIGH PASS FILTER:	When on, frequencies below 120Hz are attenuated by 12dB per octave: -12dB @120Hz -24dB @60Hz -36dB @30Hz
INPUT SATURATION:	Maximum input level is 3.9Vpp @-48dB
AUDIO THD + NOISE:	70v main output: -71dB @7.8dBu amplification; 100v main output:-72 db @8.3dBu amplification
AUDIO 2nd HARMONIC:	0.08% for 70v/100v output
POWER SOURCE:	See label near rear panel power socket: USA version: 100-120V AC, 50/60Hz, 330VA; European version: 200-240V AC, 50/60Hz, 480VA
INCLUDED ACCESSORIES:	Power cord, rack "ears"
Product Dimension	19" x 7.20 x 1U (43.6cm x 18.30cm x 4.36cm) W, D, H
Product Weight	4.7kg (10.4lbs) approx
Shipping Dimension	55.00cm x 27.60cm x 10.70cm (21.65" x 10.87" x 4.21") W, D, H
Shipping Weight	5.6kg (12.3lbs) approx

